

PD Dock Upgrade Tool User Guide

Prepare

MUST connect AC Power, USB-C and HDMI cable



Install Cypress driver at first time.

Name	Date modified	Type	Size
Cypress_Driver	11/7/2018 9:28 AM	File folder	
Setup	11/7/2018 9:28 AM	File folder	
fw_list_v1.6.7_v05.01.03.01	10/30/2018 11:22	Text Document	1 KB
Releasenote	11/6/2018 9:07 PM	Text Document	4 KB
USB-C Dock FW Upgrade Tool	11/7/2018 9:21 AM	Application	10,880 KB

Double click "Cypress_Driver.bat"


Name	Date modified	Type	Size
Cypress_Driver	9/20/2018 5:31 PM	Windows Batch File	1 KB
CypressDriverInstaller_1	2/4/2016 11:10 AM	Application	21,212 KB
CypressGx3DriverInstaller		Application	6,092 KB

Type: Windows Batch File
Size: 69 bytes
Date modified: 9/20/2018 5:31 PM

(If computer required restart, restart first and continue below upgrade steps.)

FW Upgrade

Step 1: Double click "USB-C Dock FW Upgrade Tool.exe"




Step 2: Read the instruction and click "OK (Button)"




Step 3: Read the instruction and click "OK (Button)"




Step 4: If dock not connect ready, button will be grayed out and show message “Detecting Dock... if wait too long, try re-plug USB-C cable.”



Step 5: After dock connected, click “UPGRADE (Button)”




Step 6: During upgrade process.




Step 7: Re-plug USB-C cable, wait 3 second and click "OK (Button)" to continue upgrade procedure. (This might not appear every time.)



Step 8: Update finished, click "OK (Button)"




Step 9: Read output text to confirm upgrade success.




Check Version

Step 1: After monitor displayed, click "Check Version (Button)"



Step 2: Read Version (Product Name and Versions are depends on different FW)



Step 3: Re-plug USB-C cable, wait 3 second and click "OK (Button)" to continue upgrade procedure. (This might not appear every time.)



Step 4: Click "Exit (Button)"

