

### Each information

 Depth
 6.6"

 Width
 3.3"

 Height
 9.8"

 Gross weight
 2.00lbs

 UPC#
 085896339724

 Unit quantity
 1

#### **Case information**

 Depth
 13.6"

 Width
 10.7"

 Height
 7.7"

 Gross weight
 8.90lbs

 UPC#
 50085896339729

 Unit quantity
 4

### **Shipping Information**

Country of originTWMinimum Order Quantity4Warranty Period24Lowest possible unitCase

# General information

 Color
 Black

 Moore #
 KMW33972US

 Recycled %
 0

# Kensington

# SD3500v 5Gbps USB 3.0 Dual 2K Docking Station - HDMI/DVI-I/VGA - Windows

Make a Windows Laptop or Convertible Ultra-Productive

## K33972US

### **Product Description**

Ultra-thin laptops and 2-in-1 convertibles like the Microsoft Surface Pro offer great mobile productivity and sleek good looks. But that also means they usually come up short on connectivity ports. As a result, you're constantly plugging and unplugging peripherals. That's where the SD3500v USB 3.0 Universal Docking Station comes in. It turns one USB port into six so you have access to all your peripherals, including keyboard, mouse, printer and external hard drive. And with dual HD video output, you can add two external monitors to boost productivity. The dock's two USB 3.0 ports support super-speed data transfer of up to 5 Gbps.

### **Features**

- Best For: USB 3.0 Laptops, Ultrabooks & Windows Tablets, and Monitors that support up to 2K
- Connection Technology: USB 3.0 (DisplayLink)
- · Compatibility: Windows 7 or above, macOS 10.14
- # of Monitors Supported: 2
- Video Ports: 1 x HDMI v1.2 and 1 x DVI-I (DVI-to-VGA and DVI-to-HDMI supported with included adapters)
- Maximum Resolution Supported: Single Monitor: 1920 x 1200 @ 60Hz and Dual Monitors: 2048 x 1152 @ 60Hz
- DisplayLink driver installation required. Download software from kensington.com or via Windows update.
- · Warranty: Three-year limited warranty
- Optimized for your Windows 11 docking station needs, including support for Snap Layouts and Snap Groups
- Original Apple M1/M2/M3 Our Hybrid USB-C DisplayLink docking stations are a great alternative if you are looking for multi-monitor support on your original M1/M2/M3 MacBook. NOTE: Newer Apple devices (M1/M2/M3 Max and M1/ M2/M3 Pro, etc.) are not impacted and support multiple monitors without issue on Thunderbolt docking stations.

# **Specifications**

- Connection Technology USB-A (DisplayLink)
- Driverless No
- Additional Screen Outputs 2
- Video Ports DVI-I, HDMI, VGA

- Maximum Resolution 2K
- Operating System(s) macOS, Windows
- Number of USB Ports 6
- USB Fast Charging No

www.kensington.com

