



## SD5550T Thunderbolt™ 3 and USB-C dual 4K docking station – Windows and macOS

The perfect dock for maximum productivity and compatibility.

K38131EU

### Product Description

At last, the perfect dock for maximum productivity and compatibility has arrived. Innovatively engineered to support mixed computing environments with high transfer speed requirements, the Kensington SD5550T Thunderbolt™ 3 and USB-C dual 4K docking station plugs into the power of one – one dock for more power, more bandwidth and more compatibility. Optimise your productivity with one of the first docks to deliver the unrivalled transfer speeds of Thunderbolt 3 (up to 40 Gbps) while also supporting USB-C laptops (up to 10 Gbps). Ideal for hot-desking, 4K workspaces, video editing, graphic design or content creation, the SD5550T provides more speed, more pixels, more power and more possibilities.

### Features

- Best for: Thunderbolt 3, Thunderbolt 4 and USB-C Laptops and Monitors that support up to 4K
- Connection Technology: Thunderbolt 3 & USB-C (Thunderbolt 4 laptops supported at Thunderbolt 3 features)
- Power delivery: Supports USB-C PD 3.0 (60 W of laptop charging)
- Compatibility: Windows 10 or above, macOS 10.14 or above
- No. of monitors supported: 2 (M1/M2 Base Chipset MacBook supports only a single external display.)
- Video ports: 2x DisplayPort
- Maximum resolution supported: Thunderbolt 3 – single monitor: 4K (4096x2160@60Hz) or dual: 4K (4096x2160@60Hz) USB-C Alt Mode – single monitor: (4096x2160@30Hz) or dual: (1920x1080@30Hz). M1/M2 Base Chipset MacBook supports only a single external display.
- Plug & Play installation without the need for drivers or downloads.
- System requirements: Compatible with laptops equipped with Thunderbolt 3 or Thunderbolt 4 and USB-C ports supporting Alt Mode; not backwards compatible with Thunderbolt or Thunderbolt 2. Supporting up to 40Gbps total bandwidth for Thunderbolt 3 or Thunderbolt 4 laptops and up to 10Gbps for USB-C laptops.
- Warranty: 3 Years
- Original Apple M1 - While this docking station will work with the original M1 MacBook, only a single video output is supported. For multi-monitor support on your original M1 MacBook, see our Hybrid USB-C DisplayLink docking stations (ex: SD4700P, SD4750P, SD4780P, SD4900P, etc.) or USB-A DisplayLink adapters (DisplayPort K33989, HDMI K33988, DVI-I K33974). NOTE: Newer Apple devices (M1 Max and M1 Pro, etc.) are not impacted and support multiple monitors without any issues on Thunderbolt docking stations.
- Optimised for your Windows 11 docking station needs, including support for Snap Layouts and Snap Groups.

### Specifications

- **Connection technology** Thunderbolt 3 & USB-C (Cross Platform Compatibility)
- **Driverless** Yes
- **Number of Screen Outputs** 2
- **Video ports** DisplayPort
- **Maximum resolution** 4K
- **Power delivery** 60W
- **Operating system(s)** macOS, Windows
- **Number of USB ports** 5

### Product information

**Gross weight** 1.18kg

### Retail Packaging Information

**Depth** 195mm  
**Width** 105mm  
**Height** 114mm  
**Gross weight** 1.38kg  
**UPC#** 5028252604888  
**Unit quantity** 1

### Master Case Information

**Depth** 320mm  
**Width** 210mm  
**Height** 270mm  
**Gross weight** 9.00kg  
**UPC#** 5028252604895  
**Unit quantity** 6

### Shipping Information

**Country of origin** TW  
**Minimum Order Quantity** 1

### General information

**Colour** Unknown