

# Kensington

# LD5400T Multi-User Thunderbolt 3 40Gbps Dual 4K Dock w/ K-Fob™ Smart Lock - 85W PD - Windows/macOS

Best-in-class docking with next gen locking for shared workspaces

## 39470M

#### **Product Description**

Combining a best-in-class Thunderbolt 3 docking experience with next generation laptop locking technology, Kensington delivers a game-changing 2-in-1 docking and locking solution for both Windows and Mac users. The LD5400T multi-user dock combines the productivity benefits of Thunderbolt 3 connectivity with K-Fob™ Smart Lock technology. Get more speed, more pixels, more power and more possibilities while reducing laptop theft and improving compliance with corporate security protocols. Secures thin and light laptops 11-15" in size, including models from Apple, Dell, HP, Lenovo and other manufacturers.

# **Shipping Information**

Warranty Period 24

## General information

Recycled %

#### **Features**

- Best For: Thunderbolt 3 or Thunderbolt 4 Laptops & Ultrabooks and Monitors that support up to 4K. Ideal for customer's that require Integrated Physical Security
- · Connection Technology: Thunderbolt 3 (Thunderbolt 4 laptops supported at Thunderbolt 3 features)
- USB-C power delivery: Supports USB-C PD 2.0 (85W of laptop charging)
- · Compatibility: macOS 10.13 or above, Windows 10
- No. of monitors supported: 2
- Video output: 1 x DisplayPort v1.2 and optional secondary monitor via USB-C video adapter
- Maximum resolution supported: Single monitor: 5K (5120 x 2880 @ 60Hz) and Dual monitors: 4K (4096 x 2160 @ 60 Hz)
- Plug & play installation without need for drivers or downloads
- System Requirements: Only compatible with laptops equipped with Thunderbolt 3 or Thunderbolt 4 ports; not backwards compatible with Thunderbolt 1 or Thunderbolt 2. For Windows based devices, ensure your laptop supports Power Delivery.
- · Warranty: 3 Years
- Register & Retrieve<sup>™</sup> program provides free and secure cloud-based key fob replacement.
- Apple M1 While this docking station will work with the M1 MacBook, only a single video output is supported. For
  multi-monitor support on your M1 MacBook, see our Hybrid USB-C DisplayLink docking stations (ex: SD4700P,
  SD4750P, SD4780P or SD4900P) or USB-A DisplayLink adapters (DisplayPort K33989, HDMI K33988, DVI-I
  K33974).

### **Specifications**

- Connection technology Thunderbolt 3 (Thunderbolt 4 laptops supported at Thunderbolt 3 features)
- Driverless Yes
- Number of Screen Outputs 2
- Video ports DisplayPort, USB-C

- Maximum resolution 4K
- Power delivery 85W
- Operating system(s) macOS, Windows
- Number of USB ports 4

www.kensington.com

